

JBL PD6322/66 Bi-Amp Configuration for Crown Amplifiers  
Tabulated DSP Parameters

Parameter	PD6322/66 BA LF IIR	PD6322/66 BA MHF IIR
High Pass Type	Butterworth 24dB/Oct	Butterworth 24dB/Oct
High Pass Frequency	60Hz	208Hz
Low Pass Type	Butterworth 48dB/Oct	--
Low Pass Frequency	200Hz	--
Bandpass Gain	+9.5dB	+0.5dB
Output Polarity	(+) Non-inverting	(+) Non-inverting
Output Delay	1.5ms	0.0ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	120Hz	402Hz
Filter #1 Gain	+0.5dB	-3.8dB
Filter #1 Q	Q3.5	Q2.18
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	243Hz	234Hz
Filter #2 Gain	-4.0dB	+1.9dB
Filter #2 Q	Q10.0	Q6.8
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	162Hz	4.11kHz
Filter #3 Gain	+1.5dB	-1.3dB
Filter #3 Q	Q8.0	Q5.0
Filter #4 Type	Parametric EQ	Parametric EQ
Filter #4 Frequency	200Hz	614Hz
Filter #4 Gain	+1.0dB	-4.2dB
Filter #4 Q	Q7.0	Q2.58
Filter #5 Type	--	Parametric EQ
Filter #5 Frequency	--	1.38kHz
Filter #5 Gain	--	+6.0dB
Filter #5 Q	--	Q2.36
Filter #6 Type	--	Parametric EQ
Filter #6 Frequency	--	1.94kHz
Filter #6 Gain	--	-9.1dB
Filter #6 Q	--	Q2.0
Filter #7 Type	--	Parametric EQ
Filter #7 Frequency	--	5.8kHz
Filter #7 Gain	--	+3.3dB
Filter #7 Q	--	Q5.1
Filter #8 Type	--	Parametric EQ
Filter #8 Frequency	--	11.14kHz
Filter #8 Gain	--	+3.7dB
Filter #8 Q	--	Q6.57