

JBL PD6200/66 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6200/66 MF FIR	PD6200/66 HF FIR
High Pass Type	--	--
High Pass Frequency	--	--
Low Pass Type	--	--
Low Pass Frequency	--	--
Bandpass Gain	-0.9dB	-2.9dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.1ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	888Hz	--
Filter #1 Gain	-4.4dB	--
Filter #1 Q	Q0.61	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	460Hz	--
Filter #2 Gain	-2.0dB	--
Filter #2 Q	Q1.85	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	218Hz	--
Filter #3 Gain	+1.7dB	--
Filter #3 Q	Q4.0	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	681Hz	--
Filter #4 Gain	-0.7dB	--
Filter #4 Q	Q7.0	--
Filter #5 Type	Parametric EQ	--
Filter #5 Frequency	307Hz	--
Filter #5 Gain	-0.7dB	--
Filter #5 Q	Q6.6	--