

JBL PD6200/64 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6200/64 MHF IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	205Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+1dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	357Hz
Filter #1 Gain	-2.2dB
Filter #1 Q	Q3.2
Filter #2 Type	Parametric EQ
Filter #2 Frequency	589Hz
Filter #2 Gain	-4.2dB
Filter #2 Q	Q1.32
Filter #3 Type	Parametric EQ
Filter #3 Frequency	1.07kHz
Filter #3 Gain	+2.1dB
Filter #3 Q	Q2.9
Filter #4 Type	Parametric EQ
Filter #4 Frequency	3kHz
Filter #4 Gain	-4.3dB
Filter #4 Q	Q2.35
Filter #5 Type	Parametric EQ
Filter #5 Frequency	4.65kHz
Filter #5 Gain	-1.6dB
Filter #5 Q	Q4.7
Filter #6 Type	Parametric EQ
Filter #6 Frequency	8.79kHz
Filter #6 Gain	-4.6dB
Filter #6 Q	Q1.17
Filter #7 Type	Parametric EQ
Filter #7 Frequency	12.5kHz
Filter #7 Gain	+9.1dB
Filter #7 Q	Q4.75
Filter #8 Type	Parametric EQ
Filter #8 Frequency	1.86kHz

Filter #8 Gain Filter #8 Q	-5.4dB Q2.0
Filter #9 Type Filter #9 Frequency Filter #9 Gain Filter #9 Q	Parametric EQ 533Hz -1.8dB Q13.4