

JBL PD6200/95 Bi-Amp IIR Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6200/95 MF IIR	PD6200/95 HF IIR
High Pass Type	24 But	48 L-R
High Pass Frequency	205Hz	2kHz
Low Pass Type	48 But	Out
Low Pass Frequency	1.77kHz	--
Bandpass Gain	-0.5dB	0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.906ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	550Hz	3.54kHz
Filter #1 Boost/Cut	-3.1dB	-7.5dB
Filter #1 Width	1.56 Oct	0.75 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	654Hz	13.1kHz
Filter #2 Boost/Cut	-1.1dB	+9.7dB
Filter #2 Width	0.15 Oct	0.41 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	1.26kHz	2.36kHz
Filter #3 Boost/Cut	+1.5dB	-3.8dB
Filter #3 Width	0.29 Oct	0.28 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	1.71kHz	6.28kHz
Filter #4 Boost/Cut	+2.5dB	+1.8dB
Filter #4 Width	0.39 Oct	0.19 Oct
Filter #5 Type	Bell	Bell
Filter #5 Frequency	461Hz	3.11kHz
Filter #5 Boost/Cut	-0.4dB	-1.5dB
Filter #5 Width	0.13 Oct	0.16 Oct
Filter #6 Type	Bell	Bell
Filter #6 Frequency	387Hz	3.62kHz
Filter #6 Boost/Cut	+0.4dB	+2.6dB
Filter #6 Width	0.57 Oct	0.12 Oct
Filter #7 Type	--	Bell
Filter #7 Frequency	--	14.2kHz
Filter #7 Boost/Cut	--	-4.3dB
Filter #7 Width	--	0.09 Oct

Filter #9 Type	--	Bell	
Filter #9 Frequency	--	1.62kHz	
Filter #9 Boost/Cut	--	+3dB	
Filter #9 Width	--	0.57 Oct	