

JBL PD6322/95 Tri-Amp Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6322/95 TA LF IIR	PD6322/95 TA MF IIR	PD6322/95 TA HF IIR
High Pass Type	Butterworth 24dB/Oct	Butterworth 24dB/Oct	Linkwitz-Riley 48dB/Oct
High Pass Frequency	60Hz	205Hz	2.0kHz
Low Pass Type	Butterworth 48dB/Oct	Butterworth 48dB/Oct	--
Low Pass Frequency	200Hz	1.78kHz	--
Bandpass Gain	+10.0dB	+2.0dB	+2.0dB
Output Polarity	(+) Non-inverting	(+) Non-inverting	(+) Non-inverting
Output Delay	1.302ms	0.0ms	0.906ms
Filter #1 Type	Bell	Bell	Bell
Filter #1 Frequency	117Hz	625Hz	3.36kHz
Filter #1 Boost/Cut	+0.4dB	-5.6dB	-7.6dB
Filter #1 Width	0.26 Oct	3.28 Oct	0.80 Oct
Filter #2 Type	Bell	Bell	Bell
Filter #2 Frequency	186Hz	646Hz	13.2kHz
Filter #2 Boost/Cut	+2.4dB	-1.8dB	+7.5dB
Filter #2 Width	0.34 Oct	0.22 Oct	0.38 Oct
Filter #3 Type	Bell	Bell	Bell
Filter #3 Frequency	243Hz	1.28kHz	3.11kHz
Filter #3 Boost/Cut	-4.3dB	+1.2dB	-2.3dB
Filter #3 Width	0.13 Oct	0.20 Oct	2.59 Oct
Filter #4 Type	Bell	Bell	Bell
Filter #4 Frequency	167Hz	1.66kHz	2.35kHz
Filter #4 Boost/Cut	+0.5dB	+2.2dB	-2.4dB
Filter #4 Width	0.31 Oct	0.66 Oct	0.23 Oct
Filter #5 Type	Bell	Bell	Bell
Filter #5 Frequency	172Hz	566Hz	6.32kHz
Filter #5 Boost/Cut	-1.0dB	+2.0dB	+1.2dB
Filter #5 Width	0.16 Oct	0.51 Oct	0.21 Oct
Filter #6 Type	--	Bell	Bell
Filter #6 Frequency	--	358Hz	3.11kHz
Filter #6 Boost/Cut	--	+2.0dB	-0.8dB
Filter #6 Width	--	0.13 Oct	0.10 Oct
Filter #7 Type	--	Bell	Bell
Filter #7 Frequency	--	273Hz	3.6kHz
Filter #7 Boost/Cut	--	+2.3dB	+2.7dB
Filter #7 Width	--	0.25 Oct	0.12 Oct
Filter #8 Type	--	Bell	Bell
Filter #8 Frequency	--	300Hz	14.3kHz
Filter #8 Boost/Cut	--	-1.2dB	-4.0dB
Filter #8 Width	--	0.15 Oct	0.08 Oct