

JBL PD6212/64 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6212/64 LF	PD6212/64 HF
High Pass Type	Butterworth 24dB/oct	--
High Pass Frequency	76.8Hz	--
Low Pass Type	Linear Phase 48dB/oct (FIR)	--
Low Pass Frequency	1.15kHz	--
Bandpass Gain	+2.5dB	+2.5dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.45ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	138Hz	--
Filter #1 Gain	+2.8dB	--
Filter #1 Q	Q2.76	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	175Hz	--
Filter #2 Gain	+1.6dB	--
Filter #2 Q	Q5.2	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	275Hz	--
Filter #3 Gain	-2.5dB	--
Filter #3 Q	Q4.5	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	340Hz	--
Filter #4 Gain	-1.2dB	--
Filter #4 Q	Q3.3	--
Filter #5 Type	Parametric EQ	--
Filter #5 Frequency	450Hz	--
Filter #5 Gain	+1.2dB	--
Filter #5 Q	Q2.3	--
Filter #6 Type	Parametric EQ	--
Filter #6 Frequency	507Hz	--
Filter #6 Gain	-3.0dB	--
Filter #6 Q	Q1.0	--
Filter #7 Type	Parametric EQ	--
Filter #7 Frequency	640Hz	--
Filter #7 Gain	-6.7dB	--
Filter #7 Q	Q3.1	--
Filter #8 Type	Parametric EQ	--
Filter #8 Frequency	1093Hz	--

Filter #8 Gain	+10.3dB	--
Filter #8 Q	Q1.78	--