

JBL PD6200/95 Bi-Amp IIR Rotated Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/95-H MF IIR	PD6200/95-H HF IIR
High Pass Type	Butterworth 24dB/oct	Linkwitz-Riley 48dB/oct
High Pass Frequency	205Hz	2kHz
Low Pass Type	Butterworth 48dB/oct	--
Low Pass Frequency	1.775kHz	--
Bandpass Gain	-0.5dB	0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.91ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	551Hz	3.57kHz
Filter #1 Gain	-2.7dB	-8.0dB
Filter #1 Q	Q0.52	Q1.73
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	656Hz	13.16kHz
Filter #2 Gain	-1.4dB	+9.6dB
Filter #2 Q	Q7.1	Q3.1
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	1.22kHz	2.36kHz
Filter #3 Gain	+1.1dB	-3.8dB
Filter #3 Q	Q4.3	Q4.5
Filter #4 Type	Parametric EQ	Parametric EQ
Filter #4 Frequency	1.78kHz	6.21kHz
Filter #4 Gain	+3.3dB	+1.6dB
Filter #4 Q	Q3.1	Q6.4
Filter #5 Type	Parametric EQ	Parametric EQ
Filter #5 Frequency	462Hz	3.13kHz
Filter #5 Gain	-0.7dB	-1.7dB
Filter #5 Q	Q5.9	Q7.3
Filter #6 Type	Parametric EQ	Parametric EQ
Filter #6 Frequency	507Hz	3.63kHz
Filter #6 Gain	+0.6dB	+2.6dB
Filter #6 Q	Q1.5	Q10.3
Filter #7 Type	--	Parametric EQ
Filter #7 Frequency	--	14.25kHz
Filter #7 Gain	--	-4.3dB
Filter #7 Q	--	Q14.3