

JBL PD6212/95 Bi-Amp IIR Rotated Configuration for BSS London Blu  
Tabulated DSP Parameters

Parameter	PD6212/95-H LF IIR	PD6212/95-H HF IIR
High Pass Type	24 But	48 But
High Pass Frequency	76.7Hz	1kHz
Low Pass Type	24 L-R	--
Low Pass Frequency	1.1kHz	--
Bandpass Gain	+3.5dB	+3.3dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	.740ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	137.5Hz	2kHz
Filter #1 Boost/Cut	+5.5dB	-8.7dB
Filter #1 Width	0.53 Oct	1.56 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	225Hz	1.97kHz
Filter #2 Boost/Cut	+2.6dB	+2.0dB
Filter #2 Width	0.14 Oct	0.17 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	281Hz	7.88kHz
Filter #3 Boost/Cut	-3.4dB	+5.1dB
Filter #3 Width	0.16 Oct	0.12 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	352Hz	6.18kHz
Filter #4 Boost/Cut	-3.8dB	+1.7dB
Filter #4 Width	0.61 Oct	0.14 Oct
Filter #5 Type	Bell	Bell
Filter #5 Frequency	493Hz	2.87kHz
Filter #5 Boost/Cut	+0.3dB	+2.9dB
Filter #5 Width	0.15 Oct	0.09 Oct
Filter #6 Type	Bell	Bell
Filter #6 Frequency	596Hz	2.83kHz
Filter #6 Boost/Cut	-2.1dB	-1.3dB
Filter #6 Width	0.42 Oct	0.21 Oct
Filter #7 Type	Bell	Bell
Filter #7 Frequency	690Hz	1.4kHz
Filter #7 Boost/Cut	+0.6dB	+1.0dB
Filter #7 Width	0.11 Oct	0.16 Oct
Filter #8 Type	Bell	Bell
Filter #8 Frequency	892Hz	5kHz
Filter #8 Boost/Cut	+4.7dB	+0.7dB

Filter #8 Width	0.15 Oct	0.66 Oct
-----------------	----------	----------