

JBL PD6322/66 Bi-Amp Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6322/66 BA LF IIR	PD6322/66 BA MHF IIR
High Pass Type	Butterworth 24dB/Oct	Butterworth 24dB/Oct
High Pass Frequency	60Hz	208Hz
Low Pass Type	Butterworth 48dB/Oct	--
Low Pass Frequency	200Hz	--
Bandpass Gain	+9.5dB	+0.5dB
Output Polarity	(+) Non-inverting	(+) Non-inverting
Output Delay	1.5ms	0.0ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	120Hz	402Hz
Filter #1 Boost/Cut	+0.5dB	-3.8dB
Filter #1 Width	0.36 Oct	0.57 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	243Hz	234Hz
Filter #2 Boost/Cut	-4.0dB	+1.9dB
Filter #2 Width	0.12 Oct	0.18 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	162Hz	4.11kHz
Filter #3 Boost/Cut	+1.5dB	-1.3dB
Filter #3 Width	0.16 Oct	0.25 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	200Hz	614Hz
Filter #4 Boost/Cut	+1.0dB	-4.2dB
Filter #4 Width	0.18 Oct	0.48 Oct
Filter #5 Type	--	Bell
Filter #5 Frequency	--	1.38kHz
Filter #5 Boost/Cut	--	+6.0dB
Filter #5 Width	--	0.53 Oct
Filter #6 Type	--	Bell
Filter #6 Frequency	--	1.94kHz
Filter #6 Boost/Cut	--	-9.1dB
Filter #6 Width	--	0.62 Oct
Filter #7 Type	--	Bell
Filter #7 Frequency	--	5.8kHz
Filter #7 Boost/Cut	--	+3.3dB
Filter #7 Width	--	0.24 Oct
Filter #8 Type	--	Bell
Filter #8 Frequency	--	11.1kHz
Filter #8 Boost/Cut	--	+3.7dB
Filter #8 Width	--	0.19 Oct