

JBL PD6200/95 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500  
 Tabulated DSP Parameters

Parameter	PD6200/95 MHF IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	205Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	-0.6dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	645Hz
Filter #1 Gain	-2.2dB
Filter #1 Q	Q7.8
Filter #2 Type	Parametric EQ
Filter #2 Frequency	457Hz
Filter #2 Gain	-4.5dB
Filter #2 Q	Q2.0
Filter #3 Type	Parametric EQ
Filter #3 Frequency	3.2kHz
Filter #3 Gain	-4.6dB
Filter #3 Q	Q1.02
Filter #4 Type	Parametric EQ
Filter #4 Frequency	12.61kHz
Filter #4 Gain	+8.3dB
Filter #4 Q	Q4.7
Filter #5 Type	Parametric EQ
Filter #5 Frequency	2.35kHz
Filter #5 Gain	-2.4dB
Filter #5 Q	Q8.2
Filter #6 Type	Parametric EQ
Filter #6 Frequency	3.61kHz
Filter #6 Gain	+1.5dB
Filter #6 Q	Q11.2
Filter #7 Type	Parametric EQ
Filter #7 Frequency	893Hz
Filter #7 Gain	+1.2dB
Filter #7 Q	Q4.4
Filter #8 Type	Parametric EQ
Filter #8 Frequency	1.37kHz

Filter #8 Gain Filter #8 Q	-4.7dB Q2.48
Filter #9 Type Filter #9 Frequency Filter #9 Gain Filter #9 Q	Parametric EQ 6.14kHz +0.4dB Q5.6