

JBL PD6200/66 Passive IIR Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6200/66 MHF IIR
High Pass Type	24 But
High Pass Frequency	206Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	-0.9dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	230Hz
Filter #1 Boost/Cut	+1.5dB
Filter #1 Width	0.38 Oct
Filter #2 Type	Bell
Filter #2 Frequency	580Hz
Filter #2 Boost/Cut	-6.4dB
Filter #2 Width	1.13 Oct
Filter #3 Type	Bell
Filter #3 Frequency	1.26kHz
Filter #3 Boost/Cut	+4.0dB
Filter #3 Width	0.54 Oct
Filter #4 Type	Bell
Filter #4 Frequency	1.91kHz
Filter #4 Boost/Cut	-4.8dB
Filter #4 Width	0.29 Oct
Filter #5 Type	Bell
Filter #5 Frequency	5.73kHz
Filter #5 Boost/Cut	+2.8dB
Filter #5 Width	0.31 Oct
Filter #6 Type	Bell
Filter #6 Frequency	2.7kHz
Filter #6 Boost/Cut	-4.5dB
Filter #6 Width	1.13 Oct
Filter #7 Type	Bell
Filter #7 Frequency	11.1kHz
Filter #7 Boost/Cut	+6.9dB
Filter #7 Width	0.31 Oct
Filter #8 Type	Bell
Filter #8 Frequency	19kHz
Filter #8 Boost/Cut	-5.0dB

Filter #8 Width	0.62 Oct
-----------------	----------