

JBL PD6322/43 Bi-Amp Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6322/43 BA LF IIR	PD6322/43 BA MHF IIR
High Pass Type	Butterworth 24dB/Oct	Butterworth 24dB/Oct
High Pass Frequency	60Hz	203Hz
Low Pass Type	Butterworth 24dB/Oct	--
Low Pass Frequency	180Hz	--
Bandpass Gain	+11.5dB	+1.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	1.0ms	0.0ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	158 Hz	1.24kHz
Filter #1 Boost/Cut	+4.0dB	-3.1dB
Filter #1 Width	0.16 Oct	0.44 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	138Hz	374Hz
Filter #2 Boost/Cut	-1.0dB	-2.4dB
Filter #2 Width	0.25 Oct	0.23 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	70Hz	2.46kHz
Filter #3 Boost/Cut	+1.0dB	-6.3dB
Filter #3 Width	0.21 Oct	0.62 Oct
Filter #4 Type	--	Bell
Filter #4 Frequency	--	200Hz
Filter #4 Boost/Cut	--	+1.5dB
Filter #4 Width	--	0.5 Oct
Filter #5 Type	--	Bell
Filter #5 Frequency	--	11.7kHz
Filter #5 Boost/Cut	--	+2.6dB
Filter #5 Width	--	0.23 Oct
Filter #6 Type	--	Bell
Filter #6 Frequency	--	570Hz
Filter #6 Boost/Cut	--	-3.2dB
Filter #6 Width	--	0.73 Oct
Filter #7 Type	--	Bell
Filter #7 Frequency	--	1.64kHz
Filter #7 Boost/Cut	--	+4.0dB
Filter #7 Width	--	0.2 Oct
Filter #8 Type	--	Bell
Filter #8 Frequency	--	5.64kHz
Filter #8 Boost/Cut	--	+0.8dB
Filter #8 Width	--	0.48 Oct