

JBL PD6212/66 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6212/64 LF	PD6212/64 HF
High Pass Type	Butterworth 24dB/oct	--
High Pass Frequency	76.8Hz	--
Low Pass Type	Linear Phase 48dB/oct (FIR)	--
Low Pass Frequency	1.27kHz	--
Bandpass Gain	+2.3dB	+1.8dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.595ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	152.5Hz	--
Filter #1 Gain	+5.2dB	--
Filter #1 Q	Q1.3	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	203Hz	--
Filter #2 Gain	+0.8dB	--
Filter #2 Q	Q4.0	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	286Hz	--
Filter #3 Gain	-4.8dB	--
Filter #3 Q	Q5.2	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	436Hz	--
Filter #4 Gain	-2.3dB	--
Filter #4 Q	Q5.2	--
Filter #5 Type	Parametric EQ	--
Filter #5 Frequency	600Hz	--
Filter #5 Gain	-5.2dB	--
Filter #5 Q	Q2.2	--
Filter #6 Type	Parametric EQ	--
Filter #6 Frequency	852Hz	--
Filter #6 Gain	+6.9dB	--
Filter #6 Q	Q9.0	--
Filter #7 Type	Parametric EQ	--
Filter #7 Frequency	1029Hz	--
Filter #7 Gain	+5.2dB	--
Filter #7 Q	Q5.4	--
Filter #8 Type	Parametric EQ	--
Filter #8 Frequency	1.28kHz	--

Filter #8 Gain	+1.8dB	--
Filter #8 Q	Q3.0	--