

## AE/PD Series Connector Pin-Out Guide

**Connectors:** All models contain one (1) Neutrik Speakon® connector (either NL4 or NL8, specified below) AND one (1) set of terminal strips. Terminal strips are marked with same pinout labels as below (1+ / 1-, etc). Speakons and terminal connections are in parallel with each other and can be used for loop-through purposes.

<u>Models</u>	<u>Connector Type &amp; Pinouts</u>	<u>Crossover Mode</u>
<b>PD Series and AM High-Power 3-Ways</b>		
AM7315/xx	PD6322/xx	(bi-amp/tri-amp selectable)
	<b>NL8</b>	<b>Bi-Amp</b>
	1+ / 1-	Low
	2+ / 2-	Mid-High
	3+ / 3-	n/c
	4+ / 4-	(Thru)
		<b>Tri-Amp</b>
		Low
		Mid
		High
		(Thru)
<b>PD Series and AM Mid-Highs</b>		
AM7200/xx	PD6200/xx	(passive/bi-amp selectable)
	<b>NL4</b>	<b>Passive</b>
	1+ / 1-	Mid-High
	2+ / 2-	n/c
		<b>Bi-Amp</b>
		Mid
		High
<b>PD Series and AM 2-Ways and AC 2-Ways</b>		
AM7215/xx	PD6212/xx	(passive/bi-amp selectable)
AM7212/xx		
AM5215/xx		
AM5212/xx		
AC2215/xx		
AC2212/xx		
	<b>NL4</b>	<b>Passive</b>
	1+ / 1-	Full Range
	2+ / 2-	n/c
		<b>Bi-Amp</b>
		Low
		High
<b>PD 5122 and AL, ASB &amp; ASH Single-Driver Models</b>		
AL6115	PD5122	
ASB6112		
ASB6115		
ASB6118		
ASB7118		
ASH6118		
	<b>NL4</b>	<b>Discreet</b>
	1+ / 1-	LF
	2+ / 2-	(Thru)
<b>PD 5125 and AL &amp; ASB Dual-Driver Models</b>		
AL6125	PD5125	(parallel/discrete selectable)
ASB4128		
ASB6125		
ASB6128		
ASB6128V		
ASB7128		
	<b>NL4</b>	<b>Parallel</b>
	1+ / 1-	LF1 & LF 2
	2+ / 2-	n/c
		<b>Discrete</b>
		LF 1
		LF 2