

JBL PD6200/64 Bi-Amp IIR Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6200/64 MF IIR	PD6200/64 HF IIR
High Pass Type	24 But	48 L-R
High Pass Frequency	208Hz	1.95kHz
Low Pass Type	24 But	Out
Low Pass Frequency	1.55kHz	--
Low Pass 2 Type	12 But	--
Low Pass 2 Frequency	1.55kHz	--
Bandpass Gain	+1.0dB	+1.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	.719ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	730Hz	2.84kHz
Filter #1 Boost/Cut	-5.0dB	-4.1dB
Filter #1 Width	1.32 Oct	0.44 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	1.77kHz	3.38kHz
Filter #2 Boost/Cut	+3.5dB	-8.5dB
Filter #2 Width	0.21 Oct	1.08 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	206Hz	1.78kHz
Filter #3 Boost/Cut	+1.0dB	+2.9dB
Filter #3 Width	0.83 Oct	0.19 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	1.26kHz	2.18kHz
Filter #4 Boost/Cut	-0.8dB	-2.6dB
Filter #4 Width	0.22 Oct	0.21 Oct
Filter #5 Type	Bell	Bell
Filter #5 Frequency	333Hz	4.62kHz
Filter #5 Boost/Cut	-1.0dB	-1.2dB
Filter #5 Width	0.18 Oct	0.31 Oct
Filter #6 Type	Bell	Bell
Filter #6 Frequency	505Hz	12.5kHz
Filter #6 Boost/Cut	-0.5dB	+9.0dB
Filter #6 Width	0.17 oct	0.21 Oct
Filter #7 Type	LP Shelf	Bell
Filter #7 Slope	6dB/Oct	--
Filter #7 Frequency	400Hz	7.74kHz
Filter #7 Boost/Cut	-1.0dB	-0.9dB
Filter #7 Width	--	0.25 Oct

Filter #8 Type	Bell	Bell
Filter #8 Frequency	1.55kHz	3.55kHz
Filter #8 Boost/Cut	+3.0dB	-0.9dB
Filter #8 Width	0.57 Oct	0.08 Oct