

JBL PD6322/43 Bi-Amp Configuration for Crown Amplifiers
Tabulated DSP Parameters

Parameter	PD6322/43 BA LF IIR	PD6322/43 BA MHF IIR
High Pass Type	Butterworth 24dB/Oct	Butterworth 24dB/Oct
High Pass Frequency	60Hz	203Hz
Low Pass Type	Butterworth 24dB/Oct	--
Low Pass Frequency	180Hz	--
Bandpass Gain	+11.5dB	+1.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	1.0ms	0.0ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	158 Hz	1.24kHz
Filter #1 Gain	+4.0dB	-3.1dB
Filter #1 Q	Q8.0	Q2.83
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	138Hz	374Hz
Filter #2 Gain	-1.0dB	-2.4dB
Filter #2 Q	Q5.0	Q5.4
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	70Hz	2.46kHz
Filter #3 Gain	+1.0dB	-6.3dB
Filter #3 Q	Q6.0	Q2.0
Filter #4 Type	--	Parametric EQ
Filter #4 Frequency	--	200Hz
Filter #4 Gain	--	+1.5dB
Filter #4 Q	--	Q2.5
Filter #5 Type	--	Parametric EQ
Filter #5 Frequency	--	11.73kHz
Filter #5 Gain	--	+2.6dB
Filter #5 Q	--	Q5.5
Filter #6 Type	--	Parametric EQ
Filter #6 Frequency	--	570Hz
Filter #6 Gain	--	-3.2dB
Filter #6 Q	--	Q1.7
Filter #7 Type	--	Parametric EQ
Filter #7 Frequency	--	1.64kHz
Filter #7 Gain	--	+4.0dB
Filter #7 Q	--	Q6.2
Filter #8 Type	--	Parametric EQ
Filter #8 Frequency	--	5.64kHz
Filter #8 Gain	--	+0.8dB
Filter #8 Q	--	Q2.6