

JBL PD6200/95 Bi-Amp FIR Rotated Configuration for Crown iTech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/95-H MF FIR	PD6200/95-H HF FIR
High Pass Type	--	--
High Pass Frequency	--	--
Low Pass Type	--	--
Low Pass Frequency	--	--
Bandpass Gain	-0.5dB	0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.87ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	551Hz	--
Filter #1 Gain	-2.7dB	--
Filter #1 Q	Q0.52	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	656Hz	--
Filter #2 Gain	-1.4dB	--
Filter #2 Q	Q7.1	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	462Hz	--
Filter #3 Gain	-0.7dB	--
Filter #3 Q	Q5.9	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	507Hz	--
Filter #4 Gain	+0.6dB	--
Filter #4 Q	Q1.5	--