

JBL PD6200/95 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/95 MF FIR	PD6200/95 HF FIR
High Pass Type	--	--
High Pass Frequency	--	--
Low Pass Type	--	--
Low Pass Frequency	--	--
Bandpass Gain	-0.5dB	0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.87ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	550Hz	--
Filter #1 Gain	-3.1dB	--
Filter #1 Q	Q0.8	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	654Hz	--
Filter #2 Gain	-1.1dB	--
Filter #2 Q	Q8.4	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	461Hz	--
Filter #3 Gain	-0.4dB	--
Filter #3 Q	Q9.6	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	387Hz	--
Filter #4 Gain	+0.4dB	--
Filter #4 Q	Q2.2	--