

JBL PD6322/95 Bi-Amp Configuration for Crown Amplifiers with Rotated Horns  
Tabulated DSP Parameters

Parameter	PD6322/95-H BA LF IIR	PD6322/95-H BA MHF IIR
High Pass Type	Butterworth 24dB/Oct	Butterworth 24dB/Oct
High Pass Frequency	60Hz	205Hz
Low Pass Type	Butterworth 48dB/Oct	--
Low Pass Frequency	200Hz	--
Bandpass Gain	+10.0dB	0.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	1.3ms	0.0ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	117Hz	423Hz
Filter #1 Gain	+0.4dB	-4.1dB
Filter #1 Q	Q5.0	Q2.65
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	183Hz	667Hz
Filter #2 Gain	+2.7dB	-2.3dB
Filter #2 Q	Q3.6	Q5.2
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	243Hz	1.33kHz
Filter #3 Gain	-4.3dB	-4.5dB
Filter #3 Q	Q9.4	Q2.8
Filter #4 Type	Parametric EQ	Parametric EQ
Filter #4 Frequency	173Hz	2.83kHz
Filter #4 Gain	-0.9dB	-6.3dB
Filter #4 Q	Q8.8	Q0.92
Filter #5 Type	--	Parametric EQ
Filter #5 Frequency	--	2.3kHz
Filter #5 Gain	--	-2.8dB
Filter #5 Q	--	Q7.6
Filter #6 Type	--	Parametric EQ
Filter #6 Frequency	--	12.8kHz
Filter #6 Gain	--	+7.7dB
Filter #6 Q	--	Q4.44
Filter #7 Type	--	Parametric EQ
Filter #7 Frequency	--	1.87kHz
Filter #7 Gain	--	+3.5dB
Filter #7 Q	--	Q3.1
Filter #8 Type	--	Parametric EQ
Filter #8 Frequency	--	3.59kHz
Filter #8 Gain	--	+2.6dB
Filter #8 Q	--	Q13.0