

JBL PD6200/95 Bi-Amp IIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6200/95 MF IIR	PD6200/95 HF IIR
High Pass Type	Butterworth 24dB/oct	Linkwitz-Riley 48dB/oct
High Pass Frequency	205Hz	2kHz
Low Pass Type	Butterworth 48dB/oct	--
Low Pass Frequency	1.775kHz	--
Bandpass Gain	-0.5dB	0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.91ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	550Hz	3.54kHz
Filter #1 Gain	-3.1dB	-7.5dB
Filter #1 Q	Q0.8	Q1.66
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	654Hz	13.14kHz
Filter #2 Gain	-1.1dB	+9.7dB
Filter #2 Q	Q8.4	Q3.05
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	1.26kHz	2.36kHz
Filter #3 Gain	+1.5dB	-3.8dB
Filter #3 Q	Q4.3	Q4.4
Filter #4 Type	Parametric EQ	Parametric EQ
Filter #4 Frequency	1.71kHz	6.28kHz
Filter #4 Gain	+2.5dB	+1.8dB
Filter #4 Q	Q3.2	Q6.7
Filter #5 Type	Parametric EQ	Parametric EQ
Filter #5 Frequency	461Hz	3.11kHz
Filter #5 Gain	-0.4dB	-1.5dB
Filter #5 Q	Q9.6	Q7.6
Filter #6 Type	Parametric EQ	Parametric EQ
Filter #6 Frequency	387Hz	3.62kHz
Filter #6 Gain	+0.4dB	+2.6dB
Filter #6 Q	Q2.2	Q10.5
Filter #7 Type	--	Parametric EQ
Filter #7 Frequency	--	14.25kHz
Filter #7 Gain	--	-4.3dB
Filter #7 Q	--	Q14.3