

JBL PD6212/95 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6212/95 LF FIR	PD6212/95 HF FIR
High Pass Type	Butterworth 24dB/oct	--
High Pass Frequency	76.7Hz	--
Low Pass Type	Linear phase 24dB/oct (FIR)	--
Low Pass Frequency	1.1kHz	--
Bandpass Gain	+3.5dB	+4.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.35ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	137.5Hz	--
Filter #1 Gain	+5.5dB	--
Filter #1 Q	Q2.35	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	225Hz	--
Filter #2 Gain	+2.6dB	--
Filter #2 Q	Q8.8	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	281Hz	--
Filter #3 Gain	-3.4dB	--
Filter #3 Q	Q8.0	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	352Hz	--
Filter #4 Gain	-3.8dB	--
Filter #4 Q	Q2.05	--
Filter #5 Type	Parametric EQ	--
Filter #5 Frequency	481Hz	--
Filter #5 Gain	-0.4dB	--
Filter #5 Q	Q6.0	--
Filter #6 Type	Parametric EQ	--
Filter #6 Frequency	596Hz	--
Filter #6 Gain	-2.1dB	--
Filter #6 Q	Q3.0	--
Filter #7 Type	Parametric EQ	--
Filter #7 Frequency	690Hz	--
Filter #7 Gain	+0.6dB	--
Filter #7 Q	Q11.0	--
Filter #8 Type	Parametric EQ	--
Filter #8 Frequency	898Hz	--

Filter #8 Gain	+3.7dB	--
Filter #8 Q	Q8.1	--