

JBL Professional
PD5200 /95/64/43
dbx DriveRack Tunings

PD5200/43 Bi-Amp			
	LF	MF	HF
Low Shape		But 24	But 18
Low Freq		236Hz	2.0kHz
High Shape		But 18	
High Freq		1.888Khz	Out
Phase		0 Degrees	0 Degrees
Polarity		Normal	Invert
Gain		-11.0dB	-17.0dB
Master -10.0dB			
Delay		0ms	0.56ms
LF EQ			
MF EQ			
Bell	289Hz	1.382Q	4.5dB
Bell	1.26kHz	1.382Q	2.5dB
Bell	1.89kHz	2.996Q	-3.0dB
HF EQ			
Bell	15.1kHz	.939Q	11.0dB
Bell	2.18kHz	1.382Q	2.5dB
PD5200/43 Passive			
	LF	M/HF	
Low Shape		But 24	
Low Freq		236Hz	
High Shape			
High Freq		Out	
Phase		0 Degrees	
Polarity		Normal	
Gain		-17.0dB	
Delay		0ms	
LF EQ			
M/HF EQ			
Bell	11.6kHz	.493Q	-2.5dB
Bell	19.00kHz	.826Q	8.0dB
Bell	728Hz	1.068Q	-1.5dB
Bell	1.5kHz	2.996Q	2.0dB

PD5200/64 Bi-Amp			
	LF	MF	HF
Low Shape		But 24	But 24
Low Freq		204.2Hz	2.119kHz
High Shape		But 24	
High Freq		1.498kHz	Out
Phase		0 Degrees	0 Degrees
Polarity		Normal	Normal
Gain		-2.7dB	-11.0dB
Master -10.0dB			
Delay		0ms	0.94ms
LF EQ			
MF EQ			
Bell	749Hz	.726Q	-6.0dB
Bell	289Hz	1.789Q	-2.0dB
HF EQ			
Bell	2.83kHz	2.996Q	-3.0dB
Bell	12.00kHz	.726Q	4.0dB
Bell	4.00kHz	.493Q	-1.5dB
PD5200/64 Passive			
	LF	MF	
Low Shape		But 24	
Low Freq		204.2Hz	
High Shape			
High Freq		Out	
Phase		0 Degrees	
Polarity		Normal	
Gain		-15.0dB	
Delay		0ms	
LF EQ			
M/HF EQ			
High Shelf 12dB/oct	193Hz		-2.0dB
Bell	561Hz	3.408Q	-1.0dB
Bell	4.76kHz	1.215Q	-2.0dB
Bell	315Hz	1.068Q	-1.5dB

PD5200/95 Bi-Amp			
	LF	MF	HF
Low Shape		But 24	L-R 48
Low Freq		204.2Hz	2.119kHz
High Shape		But 24	
High Freq		1.682kHz	Out
Phase		0 Degrees	0 Degrees
Polarity		Normal	Normal
Gain		-3.0dB	-12.0dB
Master -10.0dB			
Delay		0ms	.23ms
LF EQ			
MF EQ			
Bell	1.41kHz	2.315Q	3.0dB
Bell	236Hz	1.789Q	-3.0dB
Bell	667Hz	.561Q	-5.5dB
HF EQ			
Bell	15.1kHz	.335Q	8.0dB
Bell	2.12kHz	3.876Q	6.0dB
Bell	2.75kHz	2.633Q	-1.5dB
Bell	7.77kHz	.726Q	-2.5dB
PD5200/95 Passive			
	LF	MF	
Low Shape		But 24	
Low Freq		204.2Hz	
High Shape			
High Freq		Out	
Phase		0 Degrees	
Polarity		Normal	
Gain		-18.0dB	
Delay		0ms	
LF EQ			
M/HF EQ			
High Shelf 12dB/oct	297Hz		-1.0dB
Bell	11.6kHz	1.068Q	-3.5dB
Bell	19.00kHz	.939Q	9.0dB
Bell	1.83kHz	1.382Q	2.0dB

JBL Professional
PD5212 /95/64/43
dbx DriveRack Tunings

PD5212/43 Bi-Amp			
	LF	MF	HF
Low Shape		But 24	But 24
Low Freq		76.5Hz	890.9Hz
High Shape		But 18	
High Freq		943.9Hz	Out
Phase		0 Degrees	0 Degrees
Polarity		Normal	Normal
Gain		-8.0dB	-18.0dB
Master 0dB			
Delay		0ms	1.0ms
LF EQ			
MF EQ			
High Shelf 12dB/oct	223Hz		-9.0dB
Bell	315Hz	2.315Q	3.0dB
Bell	667Hz	1.789Q	-4.0dB
Bell	162Hz	2.315Q	-3.5dB
HF EQ			
Bell	2.59kHz	.638Q	-5.5dB
Bell	18.00kHz	.939Q	3.0dB
Bell	1.50kHz	1.573Q	-2.5dB
Bell	5.04kHz	1.215Q	-3.0dB
PD5212/43 Passive			
	LF	M/HF	
Low Shape		But 24	
Low Freq		76.5Hz	
High Shape			
High Freq		Out	
Phase		0 Degrees	
Polarity		Normal	
Gain		-8.2dB	
Delay		0ms	
LF EQ			
M/HF EQ			
High Shelf 12dB/oct	172Hz		-8.5dB
Bell	289Hz	1.573Q	5.0dB
Bell	1.03kHz	3.876Q	1.0dB
Bell	5.04kHz	.939Q	-1.0dB

PD5212/64 Bi-Amp			
	LF	MF	HF
Low Shape		But 24	But 24
Low Freq		76.5Hz	793.7Hz
High Shape		But 24	
High Freq		971.5Hz	Out
Phase		0 Degrees	0 Degrees
Polarity		Normal	Invert
Gain		-7.0dB	-13.0dB
Master 0dB			
Delay		0ms	1.21ms
LF EQ			
MF EQ			
High Shelf 12dB/oct	216Hz		-8.5dB
Bell	612Hz	2.315Q	-5.0dB
Bell	177Hz	3.408Q	-1.0dB
HF EQ			
Low Shelf 12dB/oct	5.50kHz		-9.0dB
Bell	1.0kHz	2.315Q	2.5dB
Bell	1.73kHz	1.573Q	-3.0dB
Bell	7.13kHz	1.573Q	-2.0dB
PD5212/64 Passive			
	LF	M/HF	
Low Shape		But 24	
Low Freq		76.5Hz	
High Shape			
High Freq		Out	
Phase		0 Degrees	
Polarity		Normal	
Gain		-7.0dB	
Delay		0ms	
LF EQ			
M/HF EQ			
High Shelf 12dB/oct	210Hz		-7.0dB
Bell	595Hz	1.573Q	-2.0dB
Bell	1.68kHz	1.573Q	-1.0dB
Bell	4.49kHz	1.573Q	-1.5dB

PD5212/95 Bi-Amp			
	LF	MF	HF
Low Shape		But 24	But 24
Low Freq		76.75Hz	840.9Hz
High Shape		But 24	
High Freq		943.9Hz	Out
Phase		0 Degrees	0 Degrees
Polarity		Normal	Normal
Gain		-6.0dB	-15.0dB
Master 0dB			
Delay		0ms	1.31ms
LF EQ			
MF EQ			
High Shelf 12dB/oct	273Hz		-12.0dB
Bell	472Hz	2.996Q	2.0dB
Bell	324Hz	3.876Q	-1.0dB
HF EQ			
Low Shelf 12dB/oct	5.04kHz		-6.5dB
Bell	6.17kHz	1.789Q	-1.5dB
Bell	1.46kHz	1.573Q	-2.5dB
Bell	1.00kHz	1.068Q	3.5dB
PD5212/95 Passive			
	LF	M/HF	
Low Shape		But 24	
Low Freq		76.5Hz	
High Shape			
High Freq		Out	
Phase		0 Degrees	
Polarity		Normal	
Gain		-3.8dB	
Delay		0ms	
LF EQ			
M/HF EQ			
High Shelf 12dB/oct	281Hz		-9.0dB
Bell	841Hz	2.996Q	-1.5dB
Bell	1.00kHz	3.408Q	2.5dB
Bell	297Hz	1.789Q	-2.5dB

JBL Professional
PD5322 /95/64/43
dbx DriveRack Tunings

PD5322/43 Tri-Amp			
	LF	MF	HF
Low Shape	But 18	But 24	But 18
Low Freq	66.2Hz	204.2Hz	2.00kHz
High Shape	But 24	But 18	
High Freq	182Hz	1.888kHz	Out
Phase	0 Degrees	0 Degrees	0 Degrees
Polarity	Normal	Normal	Invert
Gain	10.0dB	-10.0dB	-17.0dB
Master -10.0dB			
Delay	4.21ms	0ms	0.56ms
LF EQ			
Bell	111Hz	2.035Q	-4.0dB
Bell	281Hz	3.408Q	-6.0dB
Bell	182Hz	2.996Q	-1.5dB
MF EQ			
Bell	297Hz	1.382Q	4.5dB
Bell	1.26kHz	1.382Q	2.5dB
Bell	1.89kHz	2.996Q	-3.0dB
HF EQ			
Bell	15.1kHz	.939Q	11.0dB
Bell	2.18kHz	1.382Q	2.5dB
PD5322/43 Bi-Amp			
	LF	M/HF	
Low Shape	But 18	But 24	
Low Freq	66.2Hz	204.2Hz	
High Shape	But 24		
High Freq	182Hz	Out	
Phase	0 Degress	0 Degrees	
Polarity	Normal	Normal	
Gain	0.0dB	-17.0dB	
Delay	4.21ms	0ms	
LF EQ			
Bell	111Hz	2.035Q	-4.0dB
Bell	281Hz	3.408Q	-6.0dB
Bell	182Hz	2.996Q	-1.5dB
M/HF EQ			
Bell	11.6kHz	.381Q	-2.5dB
Bell	19.00kHz	.826Q	7.5dB
Bell	2.18kHz	2.996Q	-1.0dB
Bell	1.5kHz	2.996Q	2.0dB

PD5322/64 Tri-Amp			
	LF	MF	HF
Low Shape	But 18	But 24	But 24
Low Freq	60.7Hz	204.2Hz	2.119kHz
High Shape	But 24	But 24	
High Freq	182Hz	1.498kHz	Out
Phase	0 Degrees	0 Degrees	0 Degrees
Polarity	Normal	Normal	Normal
Gain	7.2dB	-2.7dB	-11.0dB
Master -10.0dB			
Delay	3.81ms	0ms	.96ms
LF EQ			
Bell	108Hz	1.382Q	-4.5dB
Bell	243Hz	2.996Q	-3.0dB
Bell	297Hz	3.876Q	-7.0dB
MF EQ			
Bell	749Hz	.726Q	-6.0dB
Bell	289Hz	1.789Q	-2.5dB
HF EQ			
Bell	2.83kHz	2.996Q	-3.0dB
Bell	12.00kHz	.726Q	4.0dB
Bell	4.00kHz	.493Q	-1.5dB
PD5322/64 Bi-Amp			
	LF	M/HF	
Low Shape	But 18	But 24	
Low Freq	60.7Hz	204.2Hz	
High Shape	But 24		
High Freq	182Hz	Out	
Phase	0 Degress	0 Degrees	
Polarity	Normal	Normal	
Gain	-1.2dB	-15.0dB	
Delay	3.81ms	0ms	
LF EQ			
Bell	108Hz	1.382Q	-4.5dB
Bell	243Hz	2.996Q	-3.0dB
Bell	297Hz	3.876Q	-7.0dB
M/HF EQ			
High Shelf 12dB/oct	193Hz		-2.0dB
Bell	561Hz	3.408Q	-1.0dB
Bell	4.76kHz	1.215Q	-2.0dB
Bell	315Hz	1.068Q	-1.5dB

PD5322/95 Tri-Amp			
	LF	MF	HF
Low Shape	But 18	But 24	L-R 48
Low Freq	60.7Hz	204.2Hz	2.119kHz
High Shape	But 24	But 24	
High Freq	182Hz	1.682kHz	Out
Phase	0 Degrees	0 Degrees	0 Degrees
Polarity	Normal	Normal	Normal
Gain	9.0dB	-3.0dB	-12.0dB
Master -10.0dB			
Delay	3.9ms	0ms	.29ms
LF EQ			
Bell	108Hz	1.382Q	-4.5dB
Bell	243Hz	2.996Q	-3.0dB
Bell	297Hz	3.876Q	-7.0dB
MF EQ			
Bell	1.41kHz	1.573Q	3.0dB
Bell	236Hz	1.789Q	-3.5dB
Bell	667Hz	.561Q	-5.0dB
HF EQ			
Bell	15.1kHz	.335Q	8.0dB
Bell	2.12kHz	3.408Q	6.0dB
Bell	2.52kHz	1.573Q	-2.5dB
Bell	8.98kHz	2.315Q	-3.5dB
PD5322/95 Bi-Amp			
	LF	M/HF	
Low Shape	But 18	But 24	
Low Freq	60.7Hz	204.2Hz	
High Shape	But 24		
High Freq	182Hz	Out	
Phase	0 Degress	0 Degrees	
Polarity	Normal	Normal	
Gain	-1.0dB	-18.0dB	
Delay	3.9ms	0ms	
LF EQ			
Bell	108Hz	1.382Q	-4.5dB
Bell	243Hz	2.996Q	-3.0dB
Bell	297Hz	3.876Q	-7.0dB
M/HF EQ			
High Shelf 12dB/oct	297Hz		-1.0dB
Bell	11.6kHz	1.068Q	-3.5dB
Bell	19.00kHz	.939Q	9.0dB
Bell	1.83kHz	1.382Q	2.0dB