

JBL PD6200/43 Bi-Amp IIR Configuration for Crown ITech HD & ITHD 4x3500  
 Tabulated DSP Parameters

Parameter	PD6200/43 MF IIR	PD6200/43 HF IIR
High Pass Type	Butterworth 24dB/oct	Linkwitz-Riley 48dB/oct
High Pass Frequency	203Hz	1.8kHz
Low Pass Type	Butterworth 36dB/oct	--
Low Pass Frequency	1.62kHz	--
Bandpass Gain	+1.0dB	+1.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	.71ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	813Hz	2.84kHz
Filter #1 Gain	-4.4dB	-12.9dB
Filter #1 Q	Q0.82	Q0.99
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	1.44kHz	12.69kHz
Filter #2 Gain	-1.6dB	+5.6dB
Filter #2 Q	Q1.8	Q2.0
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	1.8kHz	1.83kHz
Filter #3 Gain	+1.8dB	-0.6dB
Filter #3 Q	Q2.3	Q1.7
Filter #4 Type	Parametric EQ	Parametric EQ
Filter #4 Frequency	2.08kHz	8.3kHz
Filter #4 Gain	+1.3dB	-1.1dB
Filter #4 Q	Q2.2	Q2.6
Filter #5 Type	LF Shelf EQ	Parametric EQ
Filter #5 Frequency	300Hz	3.51kHz
Filter #5 Gain	-4.0dB	+1.0dB
Filter #5 Q	Q3.0	Q14.3
Filter #6 Type	LF Shelf EQ	Parametric EQ
Filter #6 Frequency	800Hz	9.38kHz
Filter #6 Gain	+2.5dB	-1.1dB
Filter #6 Q	Q6.0	Q14.4
Filter #7 Type	Parametric EQ	Parametric EQ
Filter #7 Frequency	415hz	4.5kHz
Filter #7 Gain	-2.6dB	-0.4dB
Filter #7 Q	Q2.8	Q5.3
Filter #8 Type	Parametric EQ	--
Filter #8 Frequency	590Hz	--

Filter #8 Gain	-2.5dB	--
Filter #8 Q	Q3.3	--