

JBL PD6200/95 Bi-Amp IIR Rotated Configuration for BSS London Blu  
Tabulated DSP Parameters

Parameter	PD6200/95-H MF IIR	PD6200/95-H HF IIR
High Pass Type	24 But	48 L-R
High Pass Frequency	205Hz	2kHz
Low Pass Type	48 But	Out
Low Pass Frequency	1.77kHz	--
Bandpass Gain	-0.5dB	0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.906ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	551Hz	3.57kHz
Filter #1 Boost/Cut	-2.7dB	-8.0dB
Filter #1 Width	2.39 Oct	0.72 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	656Hz	13.2kHz
Filter #2 Boost/Cut	-1.4dB	+9.6dB
Filter #2 Width	0.18 Oct	0.40 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	1.22kHz	2.36kHz
Filter #3 Boost/Cut	+1.1dB	-3.8dB
Filter #3 Width	0.29 Oct	0.28 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	1.78kHz	6.21kHz
Filter #4 Boost/Cut	+3.3dB	+1.6dB
Filter #4 Width	0.40 Oct	0.19 Oct
Filter #5 Type	Bell	Bell
Filter #5 Frequency	462Hz	3.13kHz
Filter #5 Boost/Cut	-0.7dB	-1.7dB
Filter #5 Width	0.21 Oct	0.17 Oct
Filter #6 Type	Bell	Bell
Filter #6 Frequency	507Hz	3.63kHz
Filter #6 Boost/Cut	+0.6dB	+2.6dB
Filter #6 Width	0.83 Oct	0.12 Oct
Filter #7 Type	--	Bell
Filter #7 Frequency	--	14.2kHz
Filter #7 Boost/Cut	--	-4.3dB
Filter #7 Width	--	0.09 Oct

Filter #9 Type	--	Bell	
Filter #9 Frequency	--	1.62kHz	
Filter #9 Boost/Cut	--	+3dB	
Filter #9 Width	--	0.57 Oct	