

JBL PD6200/66 Bi-Amp IIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6200/66 MF IIR	PD6200/66 HF IIR
High Pass Type	Butterworth 24dB/oct	Butterworth 48dB/oct
High Pass Frequency	208Hz	1.5kHz
Low Pass Type	Butterworth 48dB/oct	--
Low Pass Frequency	1.45kHz	--
Bandpass Gain	-0.9dB	-2.9dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.1ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	888Hz	2.48kHz
Filter #1 Gain	-4.4dB	-8.8dB
Filter #1 Q	Q0.61	Q1.71
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	1.4kHz	11.19kHz
Filter #2 Gain	+1.4dB	+10.8dB
Filter #2 Q	Q1.2	Q5.7
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	460Hz	4.18kHz
Filter #3 Gain	-2.0dB	-2.4dB
Filter #3 Q	Q1.85	Q6.09
Filter #4 Type	Parametric EQ	Parametric EQ
Filter #4 Frequency	218Hz	1.77kHz
Filter #4 Gain	+1.7dB	-2.2dB
Filter #4 Q	Q4.0	Q4.58
Filter #5 Type	Parametric EQ	Parametric EQ
Filter #5 Frequency	681Hz	5.88kHz
Filter #5 Gain	-0.7dB	+1.9dB
Filter #5 Q	Q7.0	Q6.0
Filter #6 Type	Parametric EQ	Parametric EQ
Filter #6 Frequency	307Hz	2.54kHz
Filter #6 Gain	-0.7dB	+1.9dB
Filter #6 Q	Q6.6	Q6.6
Filter #7 Type	--	Parametric EQ
Filter #7 Frequency	--	1.47kHz
Filter #7 Gain	--	-2.9dB
Filter #7 Q	--	Q4.48
Filter #8 Type	--	Parametric EQ
Filter #8 Frequency	--	8.6kHz

Filter #8 Gain	--	+2.0dB
Filter #8 Q	--	Q13.0