

JBL PD6200/95 Passive IIR Rotated Configuration for BSS London Blu  
 Tabulated DSP Parameters

Parameter	PD6200/95-H MHF IIR
High Pass Type	24 But
High Pass Frequency	207Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	-0.6dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	650Hz
Filter #1 Boost/Cut	-1.9dB
Filter #1 Width	0.11 Oct
Filter #2 Type	Bell
Filter #2 Frequency	447Hz
Filter #2 Boost/Cut	-4.3dB
Filter #2 Width	0.71 Oct
Filter #3 Type	Bell
Filter #3 Frequency	3.36kHz
Filter #3 Boost/Cut	-5.1dB
Filter #3 Width	1.04 Oct
Filter #4 Type	Bell
Filter #4 Frequency	12.4kHz
Filter #4 Boost/Cut	+8.1dB
Filter #4 Width	0.23 Oct
Filter #5 Type	Bell
Filter #5 Frequency	2.35kHz
Filter #5 Boost/Cut	-2.5dB
Filter #5 Width	0.15 Oct
Filter #6 Type	Bell
Filter #6 Frequency	3.63kHz
Filter #6 Boost/Cut	+1.6dB
Filter #6 Width	0.10 Oct
Filter #7 Type	Bell
Filter #7 Frequency	889Hz
Filter #7 Boost/Cut	+1.1dB
Filter #7 Width	0.24 Oct
Filter #8 Type	Bell
Filter #8 Frequency	1.37kHz
Filter #8 Boost/Cut	-5.6dB

Filter #8 Width	0.42 Oct
Filter #9 Type	Bell
Filter #9 Frequency	5.55kHz
Filter #9 Boost/Cut	+0.3dB
Filter #9 Width	0.18 Oct
Filter #10 Type	Bell
Filter #10 Frequency	1.92kHz
Filter #10 Gain	+0.5dB
Filter #10 Q	0.17 Oct