

JBL PD6200/64 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500  
Tabulated DSP Parameters

Parameter	PD6200/64 MF FIR	PD6200/64 HF FIR
High Pass Type	--	--
High Pass Frequency	--	--
Low Pass Type	--	--
Low Pass Frequency	--	--
Bandpass Gain	+1.0dB	+1.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.80ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	730Hz	--
Filter #1 Gain	-5.0dB	--
Filter #1 Q	Q0.94	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	206Hz	--
Filter #2 Gain	+1.0dB	--
Filter #2 Q	Q1.5	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	333Hz	--
Filter #3 Gain	-1.0dB	--
Filter #3 Q	Q7.0	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	505Hz	--
Filter #4 Gain	-0.5dB	--
Filter #4 Q	Q7.3	--
Filter #5 Type	LP Shelf EQ	--
Filter #5 Frequency	400Hz	--
Filter #5 Gain	-1.0dB	--
Filter #5 Q	Q6.0	--