

JBL PD6200/66 Bi-Amp IIR Rotated Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6200/66-H MF IIR	PD6200/66-H HF IIR
High Pass Type	24 But	48 But
High Pass Frequency	208Hz	1.5kHz
Low Pass Type	48 But	Out
Low Pass Frequency	1.45kHz	--
Bandpass Gain	-0.9dB	-2.9dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.104ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	888Hz	2.48kHz
Filter #1 Boost/Cut	-4.4dB	-8.8dB
Filter #1 Width	2.04 Oct	0.73 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	1.4kHz	11.2kHz
Filter #2 Boost/Cut	+1.4dB	+10.8dB
Filter #2 Width	1.04 Oct	0.22 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	460Hz	4.18kHz
Filter #3 Boost/Cut	-2.0dB	-2.4dB
Filter #3 Width	0.67 Oct	0.20 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	218Hz	1.77kHz
Filter #4 Boost/Cut	+1.7dB	-2.2dB
Filter #4 Width	0.31 Oct	0.27 Oct
Filter #5 Type	Bell	Bell
Filter #5 Frequency	681Hz	5.88kHz
Filter #5 Boost/Cut	-0.7dB	+1.9dB
Filter #5 Width	0.18 Oct	0.21 Oct
Filter #6 Type	Bell	Bell
Filter #6 Frequency	307Hz	2.54kHz
Filter #6 Boost/Cut	-0.7dB	+1.9dB
Filter #6 Width	0.19 Oct	0.19 Oct
Filter #7 Type	--	Bell
Filter #7 Frequency	--	1.47kHz
Filter #7 Boost/Cut	--	-2.9dB
Filter #7 Width	--	0.28 Oct
Filter #8 Type	--	Bell
Filter #8 Frequency	--	8.6kHz
Filter #8 Boost/Cut	--	+2.0dB

Filter #8 Width	--	0.10 Oct
-----------------	----	----------