

JBL PD6200/66 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/66 MHF IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	206Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	-0.9dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	230Hz
Filter #1 Gain	+1.5dB
Filter #1 Q	Q3.3
Filter #2 Type	Parametric EQ
Filter #2 Frequency	580Hz
Filter #2 Gain	-6.4dB
Filter #2 Q	Q1.1
Filter #3 Type	Parametric EQ
Filter #3 Frequency	1.26kHz
Filter #3 Gain	+4.0dB
Filter #3 Q	Q2.3
Filter #4 Type	Parametric EQ
Filter #4 Frequency	1.91kHz
Filter #4 Gain	-4.8dB
Filter #4 Q	Q4.3
Filter #5 Type	Parametric EQ
Filter #5 Frequency	5.73kHz
Filter #5 Gain	+2.8dB
Filter #5 Q	Q4.0
Filter #6 Type	Parametric EQ
Filter #6 Frequency	2.7kHz
Filter #6 Gain	-4.5dB
Filter #6 Q	Q1.1
Filter #7 Type	Parametric EQ
Filter #7 Frequency	11.08kHz
Filter #7 Gain	+6.9dB
Filter #7 Q	Q4.0
Filter #8 Type	Parametric EQ
Filter #8 Frequency	19kHz

Filter #8 Gain	-5.0dB
Filter #8 Q	Q2.0