

JBL PD6212/66 Bi-Amp IIR Configuration for BSS London Blu
Tabulated DSP Parameters

Parameter	PD6212/64 LF	PD6212/64 HF
High Pass Type	24 But	24 L-R
High Pass Frequency	76.8Hz	1.1kHz
Low Pass 1 Type	24 But	Out
Low Pass 1 Frequency	1.15kHz	--
Low Pass 2 Type	12 But	--
Low Pass 2 Frequency	1.15kHz	--
Bandpass Gain	+2.3dB	+1.8dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.750ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	152.5Hz	892Hz
Filter #1 Boost/Cut	+5.2dB	-1.6dB
Filter #1 Width	0.96 Oct	0.66 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	203Hz	1.13kHz
Filter #2 Boost/Cut	+0.8dB	+1.8dB
Filter #2 Width	0.31 Oct	0.39 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	286Hz	2.27kHz
Filter #3 Boost/Cut	-4.8dB	-8.4dB
Filter #3 Width	0.24 Oct	0.89 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	436Hz	2.73kHz
Filter #4 Boost/Cut	-2.3dB	+0.6dB
Filter #4 Width	0.24 Oct	0.10 Oct
Filter #5 Type	Bell	Bell
Filter #5 Frequency	600Hz	4.82kHz
Filter #5 Boost/Cut	-5.2dB	-1.7dB
Filter #5 Width	0.57 Oct	0.25 Oct
Filter #6 Type	Bell	Bell
Filter #6 Frequency	852Hz	6.22kHz
Filter #6 Boost/Cut	+6.9dB	+1.4dB
Filter #6 Width	0.14 Oct	0.16 Oct
Filter #7 Type	Bell	Bell
Filter #7 Frequency	1.03kHz	8.26kHz
Filter #7 Boost/Cut	+5.2dB	+3.4dB
Filter #7 Width	0.23 Oct	0.28 Oct
Filter #8 Type	Bell	Bell

Filter #8 Frequency	1.28kHz	10.8kHz
Filter #8 Boost/Cut	+1.8dB	+1.9dB
Filter #8 Width	0.42 Oct	0.21 Oct
Filter #9 Type	Bell	--
Filter #9 Frequency	1.15kHz	--
Filter #9 Boost/Cut	+3.0dB	--
Filter #9 Width	0.57 Oct	--