

JBL PD6200/64 Passive IIR Rotated Configuration for BSS London Blu  
 Tabulated DSP Parameters

Parameter	PD6200/64-H MHF IIR
High Pass Type	24 But
High Pass Frequency	205Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	+1dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	357Hz
Filter #1 Boost/Cut	-2.2dB
Filter #1 Width	0.39 Oct
Filter #2 Type	Bell
Filter #2 Frequency	589Hz
Filter #2 Boost/Cut	-4.2dB
Filter #2 Width	0.94 Oct
Filter #3 Type	Bell
Filter #3 Frequency	1.07kHz
Filter #3 Boost/Cut	+2.1dB
Filter #3 Width	0.43 Oct
Filter #4 Type	Bell
Filter #4 Frequency	3kHz
Filter #4 Boost/Cut	-4.3dB
Filter #4 Width	0.53 Oct
Filter #5 Type	Bell
Filter #5 Frequency	4.65kHz
Filter #5 Boost/Cut	-1.6dB
Filter #5 Width	0.26 Oct
Filter #6 Type	Bell
Filter #6 Frequency	8.79kHz
Filter #6 Boost/Cut	-4.6dB
Filter #6 Width	1.06 Oct
Filter #7 Type	Bell
Filter #7 Frequency	12.5kHz
Filter #7 Boost/Cut	+9.1dB
Filter #7 Width	0.26 Oct
Filter #8 Type	Bell
Filter #8 Frequency	1.86kHz
Filter #8 Boost/Cut	-5.4dB

Filter #8 Width	0.62 Oct
Filter #9 Type	Bell
Filter #9 Frequency	533Hz
Filter #9 Boost/Cut	-1.8dB
Filter #9 Width	0.09 Oct