

JBL PD6200/95 Passive IIR Configuration for BSS London Blu
 Tabulated DSP Parameters

Parameter	PD6200/95 MHF IIR
High Pass Type	24 But
High Pass Frequency	205Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	-0.6dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	645Hz
Filter #1 Boost/Cut	-2.2dB
Filter #1 Width	0.16 Oct
Filter #2 Type	Bell
Filter #2 Frequency	457Hz
Filter #2 Boost/Cut	-4.5dB
Filter #2 Width	0.62 Oct
Filter #3 Type	Bell
Filter #3 Frequency	3.2kHz
Filter #3 Boost/Cut	-4.6dB
Filter #3 Width	1.22 Oct
Filter #4 Type	Bell
Filter #4 Frequency	12.6kHz
Filter #4 Boost/Cut	+8.3dB
Filter #4 Width	0.26 Oct
Filter #5 Type	Bell
Filter #5 Frequency	2.35kHz
Filter #5 Boost/Cut	-2.4dB
Filter #5 Width	0.15 Oct
Filter #6 Type	Bell
Filter #6 Frequency	3.61kHz
Filter #6 Boost/Cut	+1.5dB
Filter #6 Width	0.11 Oct
Filter #7 Type	Bell
Filter #7 Frequency	893Hz
Filter #7 Boost/Cut	+1.2dB
Filter #7 Width	0.28 Oct
Filter #8 Type	Bell
Filter #8 Frequency	1.37kHz
Filter #8 Boost/Cut	-4.7dB

Filter #8 Width	0.50 Oct
Filter #9 Type	Bell
Filter #9 Frequency	6.14kHz
Filter #9 Boost/Cut	+0.4dB
Filter #9 Width	0.22 Oct