

JBL PD6212/43 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6212/43 LF FIR	PD6212/43 HF FIR
High Pass Type	Butterworth 24dB/oct	--
High Pass Frequency	76.8Hz	--
Low Pass Type	Linear phase 48dB/oct (FIR)	--
Low Pass Frequency	1.18kHz	--
Bandpass Gain	+3.5dB	+2.7dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.16ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	150Hz	--
Filter #1 Gain	-2.1dB	--
Filter #1 Q	Q3.0	--
Filter #2 Type	Parametric EQ	--
Filter #2 Frequency	240Hz	--
Filter #2 Gain	-1.8dB	--
Filter #2 Q	Q4.9	--
Filter #3 Type	Parametric EQ	--
Filter #3 Frequency	373Hz	--
Filter #3 Gain	-2.3dB	--
Filter #3 Q	Q3.5	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	534Hz	--
Filter #4 Gain	-6.0dB	--
Filter #4 Q	Q3.7	--
Filter #5 Type	Parametric EQ	--
Filter #5 Frequency	712Hz	--
Filter #5 Gain	-4.3dB	--
Filter #5 Q	Q3.2	--
Filter #6 Type	Parametric EQ	--
Filter #6 Frequency	750Hz	--
Filter #6 Gain	-0.4dB	--
Filter #6 Q	Q5.0	--
Filter #7 Type	Parametric EQ	--
Filter #7 Frequency	903Hz	--
Filter #7 Gain	+6.6dB	--
Filter #7 Q	Q5.7	--
Filter #8 Type	Parametric EQ	--
Filter #8 Frequency	1.135kHz	--

Filter #8 Gain	+8.8dB	--
Filter #8 Q	Q7.0	--