

JBL PD6212/66 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500  
 Tabulated DSP Parameters

Parameter	PD6212/66 FR FIR
High Pass Type (IIR) High Pass Frequency	Butterworth 24dB/oct 76.8Hz
Low Pass Type Low Pass Frequency	-- --
Bandpass Gain Output Polarity Output Delay	+3dB (+) Non-Inverting 0.0 ms
Filter #1 Type Filter #1 Frequency Filter #1 Gain Filter #1 Q	Parametric EQ 106Hz +2.4dB Q0.8
Filter #2 Type Filter #2 Frequency Filter #2 Gain Filter #2 Q	Parametric EQ 82.5Hz -0.9dB Q4.42
Filter #3 Type Filter #3 Frequency Filter #3 Gain Filter #3 Q	Parametric EQ 165Hz +6.4dB Q2.05
Filter #4 Type Filter #4 Frequency Filter #4 Gain Filter #4 Q	Parametric EQ 945Hz -2.0dB Q10.0
Filter #5 Type Filter #5 Frequency Filter #5 Gain Filter #5 Q	Parametric EQ 487Hz -1.7dB Q2.37
Filter #6 Type Filter #6 Frequency Filter #6 Gain Filter #6 Q	Parametric EQ 762Hz +1.5dB Q9.28
Filter #7 Type Filter #7 Frequency Filter #7 Gain Filter #7 Q	Parametric EQ 828Hz +4.2dB Q12.0
Filter #8 Type Filter #8 Frequency	Parametric EQ 912Hz

Filter #8 Gain	+6.1dB
Filter #8 Q	Q4.42