

JBL PD6200/43 Passive IIR Configuration for BSS London Blu  
Tabulated DSP Parameters

Parameter	PD6200/43 MHF IIR
High Pass Type	24 But
High Pass Frequency	203Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	+1dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	2.56kHz
Filter #1 Boost/Cut	-6.5dB
Filter #1 Width	0.69 Oct
Filter #2 Type	Bell
Filter #2 Frequency	1.26kHz
Filter #2 Boost/Cut	-2.7dB
Filter #2 Width	0.42 Oct
Filter #3 Type	Bell
Filter #3 Frequency	419Hz
Filter #3 Boost/Cut	-2.3dB
Filter #3 Width	0.63 Oct
Filter #4 Type	Bell
Filter #4 Frequency	1.66kHz
Filter #4 Boost/Cut	+3.9dB
Filter #4 Width	0.18 Oct
Filter #5 Type	Bell
Filter #5 Frequency	8.1kHz
Filter #5 Boost/Cut	-1.7dB
Filter #5 Width	0.78 Oct
Filter #6 Type	Bell
Filter #6 Frequency	240Hz
Filter #6 Boost/Cut	+1.1dB
Filter #6 Width	0.40 Oct
Filter #7 Type	Bell
Filter #7 Frequency	631Hz
Filter #7 Boost/Cut	-2.4dB
Filter #7 Width	0.86 Oct
Filter #8 Type	Bell
Filter #8 Frequency	12.7kHz
Filter #8 Boost/Cut	+3.0dB

Filter #8 Width	0.34 Oct
-----------------	----------