

JBL PD6200/66 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6200/66 MHF FIR
High Pass Type (IIR) High Pass Frequency	Butterworth 24dB/oct 206Hz
Low Pass Type Low Pass Frequency	-- --
Bandpass Gain Output Polarity Output Delay	+1dB (+) Non-Inverting 0.0 ms
Filter #1 Type Filter #1 Frequency Filter #1 Gain Filter #1 Q	Parametric EQ 230Hz +1.5dB Q3.3
Filter #2 Type Filter #2 Frequency Filter #2 Gain Filter #2 Q	Parametric EQ 580Hz -6.4dB Q1.1