

JBL PD6200/95 Passive IIR Rotated Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6200/95-H MHF IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	207Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	-0.6dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	650Hz
Filter #1 Gain	-1.9dB
Filter #1 Q	Q11.0
Filter #2 Type	Parametric EQ
Filter #2 Frequency	447Hz
Filter #2 Gain	-4.3dB
Filter #2 Q	Q1.75
Filter #3 Type	Parametric EQ
Filter #3 Frequency	3.36kHz
Filter #3 Gain	-5.1dB
Filter #3 Q	Q1.2
Filter #4 Type	Parametric EQ
Filter #4 Frequency	12.44kHz
Filter #4 Gain	+8.1dB
Filter #4 Q	Q5.4
Filter #5 Type	Parametric EQ
Filter #5 Frequency	2.35kHz
Filter #5 Gain	-2.5dB
Filter #5 Q	Q8.1
Filter #6 Type	Parametric EQ
Filter #6 Frequency	3.63kHz
Filter #6 Gain	+1.6dB
Filter #6 Q	Q13.1
Filter #7 Type	Parametric EQ
Filter #7 Frequency	889Hz
Filter #7 Gain	+1.1dB
Filter #7 Q	Q5.2
Filter #8 Type	Parametric EQ
Filter #8 Frequency	1.37kHz

Filter #8 Gain Filter #8 Q	-5.6dB Q2.94
Filter #9 Type Filter #9 Frequency Filter #9 Gain Filter #9 Q	Parametric EQ 5.55kHz +0.3dB Q7.0
Filter #10 Type Filter #10 Frequency Filter #10 Gain Filter #10 Q	Parametric EQ 1.92kHz +0.5dB Q7.4