

JBL PD6212/64 Passive IIR Configuration for BSS London Blu  
Tabulated DSP Parameters

Parameter	PD6212/64 Passive IIR
High Pass Type	24 But
High Pass Frequency	76.8Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	99Hz
Filter #1 Boost/Cut	-1.3dB
Filter #1 Width	0.21 Oct
Filter #2 Type	Bell
Filter #2 Frequency	161Hz
Filter #2 Boost/Cut	+3.7dB
Filter #2 Width	0.57 Oct
Filter #3 Type	Bell
Filter #3 Frequency	308Hz
Filter #3 Boost/Cut	-3.1dB
Filter #3 Width	0.46 Oct
Filter #4 Type	Bell
Filter #4 Frequency	630Hz
Filter #4 Boost/Cut	-1.4dB
Filter #4 Width	0.16 Oct
Filter #5 Type	Bell
Filter #5 Frequency	862Hz
Filter #5 Boost/Cut	+1.8dB
Filter #5 Width	0.15 Oct
Filter #6 Type	Bell
Filter #6 Frequency	2.4kHz
Filter #6 Boost/Cut	-1.7dB
Filter #6 Width	0.89 Oct
Filter #7 Type	Bell
Filter #7 Frequency	5.15kHz
Filter #7 Boost/Cut	-0.9dB
Filter #7 Width	0.28 Oct
Filter #8 Type	Bell
Filter #8 Frequency	7.4kHz
Filter #8 Boost/Cut	+1.1dB

Filter #8 Width	0.23 Oct
-----------------	----------