

JBL PD6200/64 Passive IIR Configuration for BSS London Blu  
Tabulated DSP Parameters

| Parameter           | PD6200/64 MHF IIR |
|---------------------|-------------------|
| High Pass Type      | 24 But            |
| High Pass Frequency | 205Hz             |
| Low Pass Type       | Out               |
| Low Pass Frequency  | --                |
| Bandpass Gain       | +1dB              |
| Output Polarity     | (+) Non-Inverting |
| Output Delay        | 0.0 ms            |
| Filter #1 Type      | Bell              |
| Filter #1 Frequency | 357Hz             |
| Filter #1 Boost/Cut | -2.2dB            |
| Filter #1 Width     | 0.39 Oct          |
| Filter #2 Type      | Bell              |
| Filter #2 Frequency | 589Hz             |
| Filter #2 Boost/Cut | -4.2dB            |
| Filter #2 Width     | 0.94 Oct          |
| Filter #3 Type      | Bell              |
| Filter #3 Frequency | 1.07kHz           |
| Filter #3 Boost/Cut | +2.1dB            |
| Filter #3 Width     | 0.43 Oct          |
| Filter #4 Type      | Bell              |
| Filter #4 Frequency | 3kHz              |
| Filter #4 Boost/Cut | -4.3dB            |
| Filter #4 Width     | 0.53 Oct          |
| Filter #5 Type      | Bell              |
| Filter #5 Frequency | 4.65kHz           |
| Filter #5 Boost/Cut | -1.6dB            |
| Filter #5 Width     | 0.26 Oct          |
| Filter #6 Type      | Bell              |
| Filter #6 Frequency | 8.79kHz           |
| Filter #6 Boost/Cut | -4.6dB            |
| Filter #6 Width     | 1.06 Oct          |
| Filter #7 Type      | Bell              |
| Filter #7 Frequency | 12.5kHz           |
| Filter #7 Boost/Cut | +9.1dB            |
| Filter #7 Width     | 0.26 Oct          |
| Filter #8 Type      | Bell              |
| Filter #8 Frequency | 1.86kHz           |
| Filter #8 Boost/Cut | -5.4dB            |

|                     |          |
|---------------------|----------|
| Filter #8 Width     | 0.62 Oct |
| Filter #9 Type      | Bell     |
| Filter #9 Frequency | 533Hz    |
| Filter #9 Boost/Cut | -1.8dB   |
| Filter #9 Width     | 0.09 Oct |