

JBL PD6212/43 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6212/43 FR FIR
High Pass Type (IIR) High Pass Frequency	Butterworth 24dB/oct 76.8Hz
Low Pass Type Low Pass Frequency	-- --
Bandpass Gain Output Polarity Output Delay	+4dB (+) Non-Inverting 0.0 ms
Filter #1 Type Filter #1 Frequency Filter #1 Gain Filter #1 Q	Parametric EQ 110Hz 1.6dB Q1.5
Filter #2 Type Filter #2 Frequency Filter #2 Gain Filter #2 Q	Parametric EQ 150Hz -2.0dB Q3.0
Filter #3 Type Filter #3 Frequency Filter #3 Gain Filter #3 Q	Parametric EQ 550Hz -4.2dB Q2.5
Filter #4 Type Filter #4 Frequency Filter #4 Gain Filter #4 Q	Parametric EQ 828Hz -1.5dB Q3.3
Filter #5 Type Filter #5 Frequency Filter #5 Gain Filter #5 Q	Parametric EQ 910Hz +4.7dB Q5.2
Filter #6 Type Filter #6 Frequency Filter #6 Gain Filter #6 Q	Parametric EQ 240Hz -1.4dB Q5.0