

JBL PD6212/95 Passive IIR Rotated Configuration for BSS London Blu
 Tabulated DSP Parameters

Parameter	PD6212/95-H FR IIR
High Pass Type	24 But
High Pass Frequency	76.7Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	97.5Hz
Filter #1 Boost/Cut	-3.1dB
Filter #1 Width	0.31 Oct
Filter #2 Type	Bell
Filter #2 Frequency	137.5Hz
Filter #2 Boost/Cut	+7.9dB
Filter #2 Width	0.83 Oct
Filter #3 Type	Bell
Filter #3 Frequency	318Hz
Filter #3 Boost/Cut	-2.2dB
Filter #3 Width	0.39 Oct
Filter #4 Type	Bell
Filter #4 Frequency	490Hz
Filter #4 Boost/Cut	+2.3dB
Filter #4 Width	0.50 Oct
Filter #5 Type	Bell
Filter #5 Frequency	7.7kHz
Filter #5 Boost/Cut	+2.3dB
Filter #5 Width	0.28 Oct
Filter #6 Type	Bell
Filter #6 Frequency	10.5kHz
Filter #6 Boost/Cut	-4.0dB
Filter #6 Width	0.30 Oct
Filter #7 Type	Bell
Filter #7 Frequency	1.1kHz
Filter #7 Boost/Cut	+1.6dB
Filter #7 Width	0.69 Oct
Filter #8 Type	Bell
Filter #8 Frequency	4.4kHz
Filter #8 Boost/Cut	+0.9dB

Filter #8 Width	0.69 Oct
-----------------	----------