

JBL PD6212/43 Passive IIR Rotated Configuration for BSS London Blu  
 Tabulated DSP Parameters

Parameter	PD6212/43-H FR IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	76.8Hz
Low Pass Type	Out
Low Pass Frequency	--
Bandpass Gain	+4dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Bell
Filter #1 Frequency	131Hz
Filter #1 Boost/Cut	-2.0dB
Filter #1 Width	0.62 Oct
Filter #2 Type	Bell
Filter #2 Frequency	242Hz
Filter #2 Boost/Cut	-1.6dB
Filter #2 Width	0.30 Oct
Filter #3 Type	Bell
Filter #3 Frequency	561Hz
Filter #3 Boost/Cut	-5.9dB
Filter #3 Width	0.42 Oct
Filter #4 Type	Bell
Filter #4 Frequency	1.01kHz
Filter #4 Boost/Cut	+2.1dB
Filter #4 Width	0.36 Oct
Filter #5 Type	Bell
Filter #5 Frequency	1.47kHz
Filter #5 Boost/Cut	-2.3dB
Filter #5 Width	0.37 Oct
Filter #6 Type	Bell
Filter #6 Frequency	2.47kHz
Filter #6 Boost/Cut	-6.4dB
Filter #6 Width	0.69 Oct
Filter #7 Type	Bell
Filter #7 Frequency	4.28kHz
Filter #7 Boost/Cut	+1.7dB
Filter #7 Width	0.25 Oct
Filter #8 Type	Bell
Filter #8 Frequency	11.6kHz
Filter #8 Boost/Cut	-4.6dB

Filter #8 Width	0.31 Oct
-----------------	----------