

JBL PD6212/43 Bi-Amp IIR Rotated Configuration for BSS London Blu  
Tabulated DSP Parameters

Parameter	PD6212/43-H LF	PD6212/43-H HF
High Pass Type	24 But	48 L-R
High Pass Frequency	76.8Hz	1.25kHz
Low Pass Type	24 But	Out
Low Pass Frequency	1.18kHz	--
Low Pass 2 Type	12 But	--
Low Pass 2 Frequency	1.18kHz	--
Bandpass Gain	+3.2dB	+4.4dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	1.875ms
Filter #1 Type	Bell	Bell
Filter #1 Frequency	150Hz	915Hz
Filter #1 Boost/Cut	-2.1dB	+2.0dB
Filter #1 Width	0.42 Oct	0.73 Oct
Filter #2 Type	Bell	Bell
Filter #2 Frequency	240Hz	1.65kHz
Filter #2 Boost/Cut	-1.8dB	-1.7dB
Filter #2 Width	0.25 Oct	0.50 Oct
Filter #3 Type	Bell	Bell
Filter #3 Frequency	373Hz	2.5kHz
Filter #3 Boost/Cut	-1.8dB	-13.0dB
Filter #3 Width	0.39 Oct	1.25 Oct
Filter #4 Type	Bell	Bell
Filter #4 Frequency	534Hz	4kHz
Filter #4 Boost/Cut	-6.5dB	+1.0dB
Filter #4 Width	0.32 Oct	0.25 Oct
Filter #5 Type	Bell	Bell
Filter #5 Frequency	712Hz	5.06kHz
Filter #5 Boost/Cut	-4.3dB	-1.0dB
Filter #5 Width	0.39 Oct	0.62 Oct
Filter #6 Type	Bell	Bell
Filter #6 Frequency	750Hz	6.4kHz
Filter #6 Boost/Cut	-0.4dB	+0.9dB
Filter #6 Width	0.25 Oct	0.38 Oct
Filter #7 Type	Bell	Bell
Filter #7 Frequency	903Hz	8.37kHz
Filter #7 Boost/Cut	+6.6dB	+3.1dB
Filter #7 Width	0.22 Oct	0.17 Oct
Filter #8 Type	Bell	Bell

Filter #8 Frequency	1.13kHz	10.6kHz
Filter #8 Boost/Cut	+8.8dB	-1.8dB
Filter #8 Width	0.18 Oct	0.62 Oct