Processor: XTA 226
Speaker Model(s): VRX928LA
Revision Date: 10/30/07

Northridge, CA

Bi-Amp Full Range:	1x VRX928LA		2x VRX928LA		3-6x VRX928LA		Xover for Sub	
OUTPUT	**LOW**	**HIGH**	**LOW**	**HIGH**	**LOW**	**HIGH**	**LOW**	**HIGH**
Output Gain	0 dB	-10 dB	0 dB	-10 dB	0 dB	-10 dB	--	--
DELAY & POLARITY								
Output Delay	0.13 ms	0.0 ms	0.13 ms	0.0 ms	0.13 ms	0.0 ms	0.0 ms	0.0 ms
Polarity	NORMAL	NORMAL	NORMAL	NORMAL	NORMAL	NORMAL	NORMAL	NORMAL
XOVER								
Output Lo Shape	BW24	BUT24	BW24	BUT24	BW24	BUT24	BW24	LR24
Output Lo Frequency	60 Hz	2 kHz	60 Hz	2 kHz	60 Hz	2 kHz	45 Hz	85 Hz
Output Hi Shape	BW24	--	BW24	--	BW24	--	LR24	--
Output Hi Frequency	1.5 kHz	--	1.5 kHz	--	1.5 kHz	--	75 Hz	--
EQ								
Output EQ1 Type	Low Shelf	High Shelf	Low Shelf	High Shelf	Low Shelf	High Shelf	Bell	
Output EQ1 Frequency	500 Hz	16 kHz	500 Hz	16 kHz	500 Hz	16 kHz	45 Hz	
Output EQ1 +/-	+5 dB	+12 dB	+5 dB	+12 dB	+5 dB	+12 dB	+2.5 dB	
Output EQ1 Bandwidth	--	--	--	--	--	--	2.5	
Output EQ2 Type	Bell	Bell	Bell	Bell	Bell	Bell		
Output EQ2 Frequency	850 Hz	2.1 kHz	850 Hz	2.1 kHz	850 Hz	2.1 kHz		
Output EQ2 +/-	-4 dB	+3 dB	-4 dB	+3 dB	-4 dB	+3 dB		
Output EQ2 Bandwidth	3	6	3	6	3	6		
Output EQ3Type		Bell		Bell		Bell		
Output EQ3 Frequency		3.2 kHz		3.2 kHz		3.2 kHz		
Output EQ3 +/-		-4 dB		-4 dB		-4 dB		
Output EQ3 Bandwidth		4		4		4		
Output EQ4 Type				High Shelf		High Shelf		
Output EQ4 Frequency				2 kHz		2 kHz		
Output EQ4 +/-				+4 dB		+8 dB		
Output EQ4 Bandwidth				--		--		

NOTES:

All tunings assume equal gain amplifiers.

For VRX928LA systems, use the suggested Xover for Sub filter as is and adjust the subwoofer gain for desired performance.