

JBL PD6200/43 Bi-Amp FIR Configuration for Crown ITech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6200/43 MF FIR	PD6200/43 HF FIR
High Pass Type	--	--
High Pass Frequency	--	--
Low Pass Type	--	--
Low Pass Frequency	--	--
Bandpass Gain	+1.0dB	+1.0dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	0.0 ms	0.83ms
Filter #1 Type	Parametric EQ	--
Filter #1 Frequency	813Hz	--
Filter #1 Gain	-4.4dB	--
Filter #1 Q	Q0.82	--
Filter #2 Type	LP Shelf EQ	--
Filter #2 Frequency	300Hz	--
Filter #2 Gain	-4.0dB	--
Filter #2 Q	Q3.0	--
Filter #3 Type	LP Shelf EQ	--
Filter #3 Frequency	800Hz	--
Filter #3 Gain	+2.5dB	--
Filter #3 Q	Q6.0	--
Filter #4 Type	Parametric EQ	--
Filter #4 Frequency	415Hz	--
Filter #4 Gain	-2.6dB	--
Filter #4 Q	Q2.8	--
Filter #5 Type	Parametric EQ	--
Filter #5 Frequency	590Hz	--
Filter #5 Gain	-2.5dB	--
Filter #5 Q	Q3.3	--