

JBL PD6212/64 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6212/64 Passive IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	76.8Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	99Hz
Filter #1 Gain	-1.3dB
Filter #1 Q	Q6.0
Filter #2 Type	Parametric EQ
Filter #2 Frequency	161.5Hz
Filter #2 Gain	+3.7dB
Filter #2 Q	Q2.2
Filter #3 Type	Parametric EQ
Filter #3 Frequency	308Hz
Filter #3 Gain	-3.1dB
Filter #3 Q	Q2.7
Filter #4 Type	Parametric EQ
Filter #4 Frequency	630Hz
Filter #4 Gain	-1.4dB
Filter #4 Q	Q7.8
Filter #5 Type	Parametric EQ
Filter #5 Frequency	862Hz
Filter #5 Gain	+1.8dB
Filter #5 Q	Q8.15
Filter #6 Type	Parametric EQ
Filter #6 Frequency	2.4kHz
Filter #6 Gain	-1.7dB
Filter #6 Q	Q1.4
Filter #7 Type	Parametric EQ
Filter #7 Frequency	5.15kHz
Filter #7 Gain	-0.9dB
Filter #7 Q	Q4.48
Filter #8 Type	Parametric EQ
Filter #8 Frequency	7.4kHz

Filter #8 Gain	+1.1dB
Filter #8 Q	Q5.39