

JBL PD6212/95 Passive IIR Configuration for Crown ITech HD & ITHD 4x3500
 Tabulated DSP Parameters

Parameter	PD6212/95 FR IIR
High Pass Type	Butterworth 24dB/oct
High Pass Frequency	76.7Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	97.5Hz
Filter #1 Gain	-3.1dB
Filter #1 Q	Q4.0
Filter #2 Type	Parametric EQ
Filter #2 Frequency	137.5Hz
Filter #2 Gain	+7.9dB
Filter #2 Q	Q1.5
Filter #3 Type	Parametric EQ
Filter #3 Frequency	318Hz
Filter #3 Gain	-2.4dB
Filter #3 Q	Q3.2
Filter #4 Type	Parametric EQ
Filter #4 Frequency	490Hz
Filter #4 Gain	+1.7dB
Filter #4 Q	Q1.5
Filter #5 Type	Parametric EQ
Filter #5 Frequency	7.7kHz
Filter #5 Gain	+2.3dB
Filter #5 Q	Q5.0
Filter #6 Type	Parametric EQ
Filter #6 Frequency	10.54kHz
Filter #6 Gain	-4.0dB
Filter #6 Q	Q4.1
Filter #7 Type	Parametric EQ
Filter #7 Frequency	1.2kHz
Filter #7 Gain	+0.9dB
Filter #7 Q	Q2.7
Filter #8 Type	Parametric EQ
Filter #8 Frequency	4.178kHz

Filter #8 Gain	+0.9dB
Filter #8 Q	Q3.5