

JBL PD6212/64 Passive FIR Configuration for Crown ITech HD & ITHD 4x3500  
 Tabulated DSP Parameters

Parameter	PD6212/64 Passive FIR
High Pass Type (IIR)	Butterworth 24dB/oct
High Pass Frequency	76.8Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+3dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	151Hz
Filter #1 Gain	+3.7dB
Filter #1 Q	Q1.55
Filter #2 Type	Parametric EQ
Filter #2 Frequency	256Hz
Filter #2 Gain	-1.9dB
Filter #2 Q	Q5.0
Filter #3 Type	Parametric EQ
Filter #3 Frequency	315Hz
Filter #3 Gain	-2.9dB
Filter #3 Q	Q3.1
Filter #4 Type	Parametric EQ
Filter #4 Frequency	630Hz
Filter #4 Gain	-1.5dB
Filter #4 Q	Q7.0
Filter #5 Type	Parametric EQ
Filter #5 Frequency	850Hz
Filter #5 Gain	+1.0dB
Filter #5 Q	Q8.61
Filter #6 Type	Parametric EQ
Filter #6 Frequency	875Hz
Filter #6 Gain	+0.8dB
Filter #6 Q	Q4.98
Filter #7 Type	Parametric EQ
Filter #7 Frequency	1kHz
Filter #7 Gain	-0.5dB
Filter #7 Q	Q8.8
Filter #8 Type	Parametric EQ
Filter #8 Frequency	1.09kHz

Filter #8 Gain	+0.3dB
Filter #8 Q	Q5.0