

JBL PD6322/64 Bi-Amp Configuration for Crown Amplifiers with Rotated Horns  
Tabulated DSP Parameters

Parameter	PD6322/64-H BA LF IIR	PD6322/64-H BA MHF IIR
High Pass Type	Butterworth 24dB/Oct	Butterworth 24dB/Oct
High Pass Frequency	60Hz	208Hz
Low Pass Type	Butterworth 48dB/Oct	--
Low Pass Frequency	200Hz	--
Bandpass Gain	+9.5dB	+1.5dB
Output Polarity	(+) Non-Inverting	(+) Non-inverting
Output Delay	1.5ms	0.0ms
Filter #1 Type	Parametric EQ	Parametric EQ
Filter #1 Frequency	118Hz	526Hz
Filter #1 Gain	+0.4dB	-5.0dB
Filter #1 Q	Q4.11	Q1.0
Filter #2 Type	Parametric EQ	Parametric EQ
Filter #2 Frequency	200Hz	3.47kHz
Filter #2 Gain	+1.5dB	-8.0dB
Filter #2 Q	Q7.33	Q0.74
Filter #3 Type	Parametric EQ	Parametric EQ
Filter #3 Frequency	243Hz	253Hz
Filter #3 Gain	-4.0dB	+3.0dB
Filter #3 Q	Q10.0	Q3.8
Filter #4 Type	Parametric EQ	Parametric EQ
Filter #4 Frequency	160Hz	1.02kHz
Filter #4 Gain	+1.1dB	+1.6dB
Filter #4 Q	Q3.6	Q4.9
Filter #5 Type	--	Parametric EQ
Filter #5 Frequency	--	1.85kHz
Filter #5 Gain	--	-2.0dB
Filter #5 Q	--	Q4.0
Filter #6 Type	--	Parametric EQ
Filter #6 Frequency	--	3.74kHz
Filter #6 Gain	--	+2.4dB
Filter #6 Q	--	Q5.2
Filter #7 Type	--	Parametric EQ
Filter #7 Frequency	--	5.32kHz
Filter #7 Gain	--	+2.8dB
Filter #7 Q	--	Q1.93
Filter #8 Type	--	Parametric EQ
Filter #8 Frequency	--	12.45kHz
Filter #8 Gain	--	+9.1dB
Filter #8 Q	--	Q7.0