

JBL PD6212/43 Passive FIR Rotated Configuration for Crown iTech HD & ITHD 4x3500
Tabulated DSP Parameters

Parameter	PD6212/43-H FR FIR
High Pass Type (IIR)	Butterworth 24dB/oct
High Pass Frequency	76.8Hz
Low Pass Type	--
Low Pass Frequency	--
Bandpass Gain	+4dB
Output Polarity	(+) Non-Inverting
Output Delay	0.0 ms
Filter #1 Type	Parametric EQ
Filter #1 Frequency	110Hz
Filter #1 Gain	1.6dB
Filter #1 Q	Q1.5
Filter #2 Type	Parametric EQ
Filter #2 Frequency	150Hz
Filter #2 Gain	-2.0dB
Filter #2 Q	Q3.0
Filter #3 Type	Parametric EQ
Filter #3 Frequency	550Hz
Filter #3 Gain	-4.2dB
Filter #3 Q	Q2.5
Filter #4 Type	Parametric EQ
Filter #4 Frequency	828Hz
Filter #4 Gain	-1.5dB
Filter #4 Q	Q3.3
Filter #5 Type	Parametric EQ
Filter #5 Frequency	910Hz
Filter #5 Gain	+4.7dB
Filter #5 Q	Q5.2
Filter #6 Type	Parametric EQ
Filter #6 Frequency	240Hz
Filter #6 Gain	-1.4dB
Filter #6 Q	Q5.0
Filter #7 Type	Parametric EQ
Filter #7 Frequency	372Hz
Filter #7 Gain	+1.5dB
Filter #7 Q	Q12.0
Filter #8 Type	Parametric EQ
Filter #8 Frequency	532Hz

Filter #8 Gain	-0.5dB
Filter #8 Q	Q4.0